



POWER BRIGHT
YOUR LEADER IN POWER SOLUTIONS

MODEL
PW1100-12

SPECIFICATION SHEET

12V DC to AC 1100 Watt Power Inverter



This inverter plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle

This unit has the following features:

- 1100 watts continuous power
- 2200 watts peak power
- Provides 9.2 Amps
- Anodized aluminum case provides durability
- Built-in Cooling Fan
- External, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch
- LED Display- Input Voltage/Output Wattage



| | |
|------------------------|----------------------------|
| Optimum efficiency | up to 90% |
| No-load draw | < 0.18 amp (12V) |
| Output Wave Form | Modified Sinewave |
| Input voltage range | 10-15 VDC |
| Over voltage shutdown | over 15 VDC |
| Under voltage shutdown | under 10 VDC |
| Low voltage alarm | Audible |
| Overload shutdown | Yes |
| Thermal shutdown | Yes |
| Short circuit shutdown | Yes |
| AC receptacle | 2 - three-prong receptacle |
| Warranty | 1 year |
| Inverter weight | 4.00 lbs |
| Dimensions (W x H x D) | 5.8 x 2.8 x 11.25 in. |
| Weight | 6 lbs. |

MODEL
PW1100-12
SPECIFICATION SHEET

www.PowerBright.com
© 2010 PowerBright . All rights reserved