



**POWER BRIGHT**  
YOUR LEADER IN POWER SOLUTIONS

MODEL  
**PW6000-12**

SPECIFICATION SHEET

## 12V DC to AC 6000 Watt Power Inverter

This heavy duty inverter plugs directly to a 12 Volt DC battery to power large appliances, air conditioners, heavy duty power tools and many other electronics in your vehicle !

### This unit has the following features:

- 6000 watts continuous power
- 12000 watts peak power
- Provides 50 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- FOUR - 3 Prong 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch

**CE** **RoHS**  
COMPLIANT



Optimum efficiency	up to 90%
No-load draw	< 0.3 amp (12V)
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	4 three-prong receptacle
Warranty	1 year
Inverter weight	28.00 lbs
Dimensions (W x H x D)	8.9 x 6.1 x 26 in.
Weight	35 lbs.

MODEL  
**PW6000-12**  
SPECIFICATION SHEET

[www.PowerBright.com](http://www.PowerBright.com)  
© 2010 PowerBright . All rights reserved