



1500 Watt Pure Sine Wave Power Inverter



Pure sine wave inverters provide premium power that is identical to or even better than power supplied by your electric company.

It plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle!


This unit has the following features:

- Pure Sine Wave Power Inverter
- 1500 watts continuous power
- 3000 watts peak power
- Anodized aluminum case provides durability
- Built-in Cooling Fan
- 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch
- Optional Remote Switch

12 VOLT DC

24 VOLT DC

| | 12 VOLT DC | 24 VOLT DC |
|------------------------|-----------------------|-----------------------|
| Output Wave Form | Pure Sine Wave | Pure Sine Wave |
| No-load draw | < 1.6 amp | < 1.6 amp |
| Harmonic Distortion | less than 3% | less than 3% |
| Input voltage range | 10 - 15 VDC | 20 - 30 VDC |
| Over voltage shutdown | over 15 VDC | over 30 VDC |
| Under voltage shutdown | under 10 VDC | under 20 VDC |
| Overload shutdown | Yes | Yes |
| Thermal shutdown | Yes | Yes |
| Short circuit shutdown | Yes | Yes |
| AC receptacle | Three GFCI 3-Prong | Three GFCI 3-Prong |
| Warranty | 1 year | 1 year |
| Inverter weight | 13.8 lbs | 13.8 lbs |
| Dimensions (W x H x D) | 11.2 x 3.9 x 16.3 in. | 11.2 x 3.9 x 16.3 in. |
| Weight | 15 lbs. | 15 lbs. |



MODIFIED SINE WAVE



PURE SINE WAVE
90% LOWER DISTORTION RATE

The benefits in going pure are:

- Lower distortion rate: between 2 to 5% harmonic distortion compared to 30 to 50% on a modified wave inverter.
- Easier start up on inductive loads and lower power consumption.
- Brighter and sharper image on monitors and TV sets
- Better sound quality on audio systems