

12V DC to AC 1500 Watt Power Inverter



This inverter plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle

This unit has the following features:

- 1500 watts continuous power
- 3000 watts peak power
- Provides 12.5 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 110 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch



Optimum efficiency	up to 90%
No-load draw	< 0.4 amp (12V)
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	2 - three-prong receptacle
Warranty	1 year
Inverter weight	8.00 lbs
Dimensions (W x H x D)	10.25 x 3.5 x 11.6 in.
Weight	11.5 lbs.