



POWERBRIGHT
YOUR LEADER IN POWER SOLUTIONS

MODEL
PW900-12

SPECIFICATION SHEET

12V DC to AC 900 Watt Power Inverter



This inverter plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle

This unit has the following features:

- 900 watts continuous power
- 1800 watts peak power
- Provides 7.5 Amps
- Anodized aluminum case provides durability
- Built-in Cooling Fan
- External, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch

CE RoHS
COMPLIANT

Optimum efficiency	up to 90%
No-load draw	< 0.9 amp
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	2 - three-prong receptacle
Warranty	1 year
Inverter weight	3.00 lbs
Dimensions (W x H x D)	5.8 x 2.8 x 10.4 in.
Weight	6 lbs.

MODEL
PW900-12
SPECIFICATION SHEET

www.PowerBright.com
© 2009 PowerBright . All rights reserved